

EF4500iSE

# KEY FEATURES

## Ease of Operation

### **Automatic Choke**

Easy starting even in cold climates

### **Electric Start**

Effortless turn the key to start

### **Fuel Gauge**

Indicates the amount of gasoline to indicate refueling intervals

### **Hour Meter**

Monitor service intervals

### **Noise Block Sound Reduction System**

Very Quiet 58 - 64 decibels

### **Power Meter**

Monitor generators supplied power

## Power

### **30 Amp Outlet**

30 Amp Outlet plug-in for more power

### **Maximum AC Output**

4500 Watts

## Protection

### **Clean Power**

Safe to use with sensitive equipment

### **CO Sensor**

Engine shuts off if a high level of carbon monoxide is detected

### **Ground Earth Terminal**

Prevents Electric Shock

### **Overload Indicator**

Alert Indicator if rated power is exceeded

## Reliability

### **3 Year Limited Warranty**

### **Low Oil Warning System**

Shuts the engine off to protect the engine if the oil level drops

### **MZ360 Engine**

Durable MZ360 Engine "Designed for long life"

# SPECIFICATIONS

Type	Brushless Inverter
Peak AC Output (MAX)	4500 watts
Continuous AC Output (Rated)	4000 watts
Engine	OHV, air-cooled, single cylinder, 4-stroke
Displacement	357cc
LxWxH	30.7in x 24.3in x 27.2in
Dry Weight	209 lbs
Fuel Tank Capacity	4.5 gal
Continuous Operation at 1/4 Rated Load	15.2 hrs
Noise Level (1/4 Load - Rated Load)	58 - 60 dBA
Warranty	3 Year Limited Warranty